

Cat. No.	Suitable Conductors kcmil/AWG		Overcurrent Protection Fuse Required Class/Max Amp Rating						SCCR, RMS Sym, kA	Volts Max
	Line	Load	J	T	RK1	RK5	G	CC		
264-311, 264-314, 264-313, 264-315, 264-316, 264-317, 264-318, 264-343, 264-345, 264-348, 264-180, 264-152, 264-153, 264-154, 264-155, 264-156, 264-157, 264-158, 264-159, 264-160, 264-161, 264-162, 264-182, 264-183, 264-184, 264-185, 264-186, 264-187, 264-188, 264-189, 264-190, 264-191, 264-192	14-12 AWG	14-12 AWG	30	30	—	—	30	30	100	600
264-321, 264-324, 264-326, 264-327, 264-131, 264-301, 264-304, 264-306, 264-307, 264-130, 264-102, 264-103, 264-104, 264-105, 264-106, 264-107, 264-108, 264-109, 264-110, 264-111, 264-112, 264-132, 264-133, 264-134, 264-135, 264-136, 264-137, 264-138, 264-139, 264-140, 264-141, 264-142	14-12 AWG	14-12 AWG	30	30	—	—	30	30	100	600
264-341, 264-344, 264-346, 264-347, 264-280, 264-252, 264-253, 264-254, 264-255, 264-256, 264-257, 264-258, 264-259, 264-260, 264-261, 264-262, 264-282, 264-283, 264-284, 264-285, 264-286, 264-287, 264-288, 264-289, 264-290, 264-291, 264-292	14-12 AWG	14-12 AWG	30	30	—	—	30	30	100	600
264-351, 264-354, 264-356, 264-357, 264-231, 264-331, 264-334, 264-336, 264-337, 264-230, 264-202, 264-203, 264-204, 264-205, 264-206, 264-207, 264-208, 264-209, 264-210, 264-211, 264-212, 264-232, 264-233, 264-234, 264-235, 264-236, 264-237, 264-238, 264-239, 264-240, 264-241, 264-242	14-12 AWG	14-12 AWG	30	30	—	—	30	30	100	600
280-519, 280-529, 280-520, 280-530, 280-527, 280-537, 280-523, 280-533, 280-524, 280-534, 280-513, 280-543, 280-549, 280-551, 280-550, 280-547, 280-557, 280-552, 280-510, 280-519/0000-0300, 280/519/0000-0400	14-12 AWG	14-12 AWG	60	60	—	—	50	30	100	600
280-601, 280-602, 280-603, 280-604, 280-621, 280-633, 280-634, 280-646, 280-650, 280-653, 280-656, 280-671, 280-672, 280-681, 280-684, 280-691, 280-830, 280-831, 280-832, 280-833, 280-834, 280-835, 280-901, 280-902, 280-903, 280-904, 280-905, 280-906, 280-946, 280-990, 280-992, 280-993, 280-994, 280-996, 280-999, 281-631, 281-651, 281-652, 281-653, 281-654, 281-663, 281-664, 281-668, 281-678, 281-679, 281-681, 281-684, 281-685, 281-686, 281-993, 281-994 and 281-998	14-12 AWG	14-12 AWG	100	100	60	30	60	30	100	600
280-603, 280-621, 280-626, 280-826, 280-989, 280-995, 281-601, 281-604, 281-691, 281-901, 281-902, 281-903, 281-904, 281-905, 281-906 and 281-992	14-12 AWG	14-12 AWG	100	100	60	30	60	30	100	600
280-607, 280-637, 280-640, 280-641, 280-651, 280-654, 280-677, 280-678, 280-687, 280-837, 280-838, 280-907, 280-998, 281-607, 281-637, 281-657, 281-658, 281-687 and 281-907	14-12 AWG	14-12 AWG	100	100	60	30	60	30	100	600
280-868, 280-869, 280-870, 280-871, 280-874, 280-875, 280-876, 280-877, 280-879, 280-880, 280-881, 280-882, 280-883, 280-884, 280-885, 280-886	14-12 AWG	14-12 AWG	30	30	—	—	30	30	100	600
281-530, 281-531, 281-532, 281-619, 281-620, 281-629, 281-630	14-12 AWG	14-12 AWG	60	60	—	—	50	30	100	600
282-601, 282-604 and 282-691	14-10 AWG	14-10 AWG	100	100	60	30	60	30	100	600
282-607, 282-681, 282-682, 282-684, 282-687, 282-901, 282-902, 282-904, 282-907, 282-992 and 282-993	14-10 AWG	14-10 AWG	100	100	60	30	60	30	100	600
282-694, 282-695, 282-697, 282-699	14-10 AWG	14-10 AWG	60	60	—	—	50	30	100	600

283-601, 283-604 and 283-691	14-6 AWG	14-6 AWG	100	100	60	30	60	30	100	600
283-607, 283-671, 283-672, 283-674, 283-677, 283-901, 283-902, 283-904, 283-907, 283-992 and 283-998	14-6 AWG	14-6 AWG	100	100	60	30	60	30	100	600
	6 AWG	6 AWG	150	150	100	60	60	30	100	600
284-601, 284-604, 284-607, 284-681, 284-682, 284-684, 284-687, 284-691, 284-901, 284-902, 284-904, 284-907, 284-992 and 284-993	14-8 AWG	14-8 AWG	100	100	60	30	60	30	100	600
284-621	2 AWG	(1) 12 w/ (2) 8	200	200	100	30	60	30	100	600
285-130, 285-131, 285-132, 285-133, 285-134, 285-135, 285-136, 285-137, 285-138, 285-139, 285-935	6-2 AWG	6-2 AWG	200	200	100	30	60	30	100	600
285-130, 285-132, 285-133, 285-135, 285-136, 285-0138 with 285-427	2-4	2-4 main 10 in power tap	200	200	100	30	60	30	100	600
285-140, 285-141, 285-142, 285-143, 285-144, 285-145, 285-146, 285-147, 285-148, 285-149, 285-150, 285-151, 285-152, 285-153, 285-154, 285-155, 285-156, 285-158, 285-159, 285-950	1/0-2/0 AWG	1/0-2/0 AWG	400	400	200	100	60	30	100	600
	6-2/0 AWG	6-2/0 AWG	200	200	100	30	60	30	100	600
285-150, 285-152, 285-153, 285-154, 285-155, 285-156, 285-157, 285-158, 285-950 with 285-447	2/0-6	2/0-6 main 10 in power tap	200	200	100	30	60	30	100	600
285-157, 285-157/999-950	1/0 AWG	1/0 AWG	400	400	200	100	60	30	100	600
	1/0-2/0 AWG	1/0-2/0 AWG	200	200	100	30	60	30	100	600
285-180, 285-181, 285-182, 285-183, 285-184, 285-185, 285-186, 285-187, 285-188, 285-189, 285-190, 285-191, 285-192, 285-193, 285-194, 285-195, 285-196, 285-198, 285-199, 285-995	1/0-3/0 AWG	1/0-3/0 AWG	300	300	200	100	60	30	100	600
285-190, 285-192, 285-193, 285-194, 285-195, 285-197, 285-995 with 285-407	4/0-4	4/0-4 main 8-6 in power tap	350	350	200	100	60	30	100	600
285-197, 285-197/999-950	3-4/0 AWG	3-4/0 AWG	400	400	200	100	60	30	100	600
285-635, 285-634, 285-992, 285-637	8-2 AWG	8-2 AWG	200	200	100	30	60	30	100	600
285-1156, 285-1158, 285-1160, 285-1161, 285-1162, 285-1163, 285-1164, 285-1165, 285-1166, 285-1167, 285-1167/0999-950, 285-1168, 285-1169, 285-1181, 285-1182, 285-1183, 285-1184, 285-1185, 285-1186, 285-1187, 285-1187/0999-950, 285-1188, 285-1189, 285-1190	350- 1/0	350- 1/0	400	400	200	100	60	30	100	600
285-1156, 285-1158, 285-1160, 285-1161, 285-1162, 285-1164, 285-1166, 285-1167, 285-1184, 285-1185, 285-1187 with 285-1175	350- 1/0	350- 1/0 main 8-6 in power tap	350	350	200	100	60	30	100	600
Terminal Block Models 769-151, 769-156, 769-171, 769-176, 769-207, 769-214 769-217, 769-227, 769-237 used with Female Plug Models 769-101 thru 769-115 and 769-121 thru 769-135	14-12 AWG	14-12 AWG	30	30	—	—	30	30	100	600
826-159 thru 826-172	14-12 AWG	14-12 AWG	60	60	30	—	60	30	100	300
828-334, 828-335	12-8 AWG	12-8 AWG	100	100	60	30	60	30	100	600

831-3202/007-000, 831-3203/007-000, 831-3204/007-000, 831-3205/007-000, 831-3206/007-000, 831-3207/007-000, 831-3208/007-000 with 831-3102, 831-3103, 831-3104, 831-4105, 831-3106, 831- 3107, 831-3108 (female could have /037-000 suffix to indicate locking lever)	12-8 AWG	12-8 AWG	60	60	30	—	60	30	100	600
862-0503, 862-0504, 862-0505, 862-0525, 862-0532, 862-0533, 862-0534, 862-0552, 862-0562, 862-0593, 862-0594, 862-0603, 862-0604, 862-0605, 862-0615, 862-0625, 862-0632, 862-0633, 862-0634, 862-0652, 862-0662, 862-0693, 862-0694, 862-1503, 862-1504, 862-1505, 862-1515, 862-1525, 862-1532, 862-1533, 862-1534, 862-1552, 862-1562, 862-1593, 862-1594, 862-1603, 862-1604, 862-1605, 862-1615, 862-1625, 862-1632, 862-1633, 862-1634, 862-1652, 862-1662, 862-1693, 862-1694, 862-2503, 862-2504, 862-2505, 862-2515, 862-2525, 862-2532, 862-2533, 862-2534, 862-2552, 862-2562, 862-2593, 862-2594, 862-2603, 862-2604, 862-2605, 862-2615, 862-2625, 862-2632, 862-2633, 862-2634, 862-2652, 862-2662, 862-2693, 862-2694, 862-8503, 862-8504, 862-8505, 862-8515, 862-8525, 862-8533, 862-8534, 862-8593, 862-8594, 862-8603, 862-8604, 862-8605, 862-8615, 862-8625, 862-8633, 862-8634, 862-8693, 862-8694, 862-9504, 862-9505, 862-9515, 862-9525, 862-9533, 862-9534, 862-9593, 862-9594, 862-9603, 862-9604, 862-9605, 862-9615, 862-9625, 862-9633, 862-9634, 862-9693, 862-9694	12 AWG	12 AWG	60	60	30	—	60	30	100	600
2001-1201, 2001-1204, 2001-1202, 2001-1207, 2001-1301, 2001-1304, 2001-1302, 2001-1307, 2001-1401, 2001-1404, 2001-1402, 2001-1407	14 AWG	14 AWG	30	30	—	—	30	30	100	600
2002-12xx, 2002-13xx, 2002-14xx, 2002-63xx, 2002-64xx, 2002-22xx, 2002-32xx	14-12 AWG	14-12 AWG	60	60	30	—	50	30	100	600
2004-13xx, 2004-14xx	14-10 AWG	14-10 AWG	60	60	30	—	50	30	100	600
2006-12xx, 2006-13xx	10-8 AWG	10-8 AWG	100	100	60	30	60	30	100	600
2006-16xx	10-8 sol/str	10-8 sol/str	100	100	60	30	60	30	100	600
2006-1681	20-8 sol/str	—	—	—	—	—	—	—	—	—
2006-1681/1000-0413, 2006-1681/1000-0434	20-8 sol/str	—	—	—	—	—	—	—	—	—
2006-1681/1000-0429, 2006-1681/1000-0449	20-8 sol/str	—	—	—	—	—	—	—	—	—
2010-12xx, 2010-13xx	10-6 AWG	10-6 AWG	100	100	60	30	60	30	100	600
2016-1201, 2016-1202, 2016-1204, 2016-1207, 2016-1301, 2016-1302, 2016-1304, 2016-1307 (9)	10-4 AWG	10-4 AWG	100	100	60	30	60	30	100	600
2022-12xx, 2022-13xx, 2022-14xx, 2022-101 through -109, 2022-22xx, 2022-161, 2022-164, 2022-167, 2022-171, 2022-174, 2022-177, 2022-181, 2022-184, 2022-187 with any suffix /000-036, /000-037, /000-038, /000-039 and /999-953	14 AWG	14 AWG	80	80	60	30	60	30	100	600
2002-26xx, 2002-24xx, 2002-16xx, 2002-18xx, 2002-29xx, 2002-17xx, 2002-19xx	12-14 AWG	12-14 AWG	60	60	30	—	50	30	100	600
2006-86xx	8-14 AWG	8-14 AWG	100	100	60	30	60	30	100	600
2201-1201, 2201-1204, 2201-1202, 2201-1207, 2201-1301, 2201-1304, 2201-1302, 2201-1307, 2201-1401, 2201-1404, 2201-1402, 2201-1407	14 AWG	14 AWG	30	30	—	—	30	30	100	600
2204-12xx, 2204-13xx, 2204-14xx	14-10 AWG	14-10 AWG	60	60	30	—	50	30	100	600

2202-12xx, 2202-13xx, 2202-14xx, 2202-1441, 2202-63xx, 2202-64xx, 2202-16xx, 2202-18xx	14-12 AWG	14-12 AWG	60	60	30	—	50	30	100	600
2202-17xx, 2202-19xx,	12-14 AWG	12-14 AWG	60	60	30	—	50	30	100	600
2206-12xx, 2206-13xx, 2206-16xx	10-8 AWG	10-8 AWG	100	100	60	30	60	30	100	600
2216-1201, 2216-1202, 2216-1204, 2016-1207, 2216-1301, 2216-1302, 2216-1304, 2216-1307	10-4 AWG	10-4 AWG	100	100	60	30	60	30	100	600
2210-12xx, 2210-13xx	10-6 AWG	10-6 AWG	100	100	60	30	60	30	100	600